

Fire Alarm Panel

JAY JE-1141



Salient Features :-

- The panel ranges from 2 to 64 zones.
- The panel complies with IS 2189 specification.
- The panel has separate fire and fault indications.
- The panel also has separate fire and common fault relay.
- The panel comprises of a 4Amp power supply unit.
- Battery backup is provided along with the AC supply.
- The panel is equipped with a 24VdC piezoelectric buzzer for fault and fire.

Synopsys Tech Pvt. Ltd.

A-001, Fressia CHS LTD, Baburao Ranade Marg, Off. L.M. Road, Behind Bank of India, Dahisar West, Mumbai-400068. Tel. 022-28904500/6800/6500 Email :- info@synopsystech.com

Technical Specifications:-

INTERNAL POWER SUPPLY UNIT

- Constant potential battery charger 14.5V DC
- Output Current limited to 3 A
- Mains supply input voltage range 230V AC + or – 10 %, 50 Hz
- Total panel quiescent current 50mA nominal
- Approx. Standby time 4.5 Ah Batt. 24 hrs.
- Battery recharge time from discharge 3 Hr. approx.

INTERNAL RELAY CONTACT RATING

- Fire Relay 5 Amp. S.P. 240 V DC

Panel Indications:-

- System ON Green LED - System normal
- Fire Red LED – MCP/Detector activated
- Zone fault Amber LED – Indicates zone wiring detector fault
- Zone fire Red LED – indicates zone where fire has been detected

EXTERNAL CONTROLS:-

- Sound To sound external as well as internal sounders
- Silence To silence external as well as internal sounders
- Reset Lamp test & resets the panels.

OPERATING TEMPERATURE

10- 49degree C

MATERIAL

M.S. POWDER COATED

CABLING

Four wire to be looped

SIZE

375 (H) mm x 300 (W) mm x 100 (D) mm

Synopsys Tech Pvt. Ltd.

A-001, Fressia CHS LTD, Baburao Ranade Marg, Off. L.M. Road, Behind Bank of India, Dahisar West, Mumbai-400068. Tel. 022-28904500/6800/6500 Email :- info@synopsysotech.com